

Flush-mounting RF receiver with roller shutter function

05-333

4 year warranty

This mini-receiver is used to control roller shutters and blinds. It is very easy to mount due to its compact dimensions. It works with both wall-mounted and hand-held transmitters. The run time is 90 seconds. With the 2-button mode, you can:

- open, close and stop the roller shutters and blinds;
- turn the vertical blind slats.

Technical characteristics:

- max. switch current: 4 A/ 230V AC;
- dimensions: L70xW49xD29mm.



Technical data

Mini receiver for flush mounting with shutter function, controlled wirelessly via radio frequency (868.3 MHz). Max. 32 transmitters per receiver. min. reception range in a building: 30 m; in open field 100 m. Dimensions: 49 x 70 x 29 mm. Max. load: 4 A. Power supply: 230 V 50 Hz. Modulation type: FSK. In accordance with Belgian and European legislation: CE marked. This product complies with all applicable European directives and regulations. For radio equipment, Niko nv declares that it complies with Directive 2014/53/EU. May be used in all European member states. Manual is included.

CE

Wiring diagram

