

Double push button with LED for Niko Home Control, sterling coated

121-52002

4 year warranty

With this push button, you can perform two operations. It is attached to the wall-mounted printed circuit board via a click mechanism. An LED indicates whether the light is switched on or off. Switch including button. Finishing colour: sterling coated.

Technical data

Double push button with LED for Niko Home Control, sterling coated.

- Material central plate: The central plate is enamelled and made of rigid PC and ASA.
- Colour: enamelled sterling (approximately NCS S 4000 - N, RAL 9007)
- Fire safety
 - the plastic parts of the central plate are self-extinguishing (comply with a filament test of 650 °C)
 - the plastic parts of the central plate are halogen-free
- Input voltage: 26 Vdc (SELV, safety extra-low voltage)
- Dismantling: To dismount simply pull the push button off the wall-mounted printed circuit board.
- Impact resistance: After mounting, an impact-resistance of IK06 is guaranteed.
- Dimensions (HxWxD): 44.5 x 44.5 x 8.6 mm
- Marking: CE

